

PRODUCT FEATURES



LAMPING

It can power lamps totaling up to 75 watts. The transformer is concealed inside a decorative housing with a fast acting secondary circuit breaker that will safely turn the system off should a short occur. Once the short has been removed the breaker can be reset.

Kable Lite Surface Transformer-75W Mag



Kable Lite Surface Transformer-75W Mag

ORDERING INFORMATION

700SRT75D FINISH

S SATIN NICKEL

As a general rule when using LED fixtures we do not recommend using greater than 70% of specified maximum wattage on the transformer due to inrush current. for assistance, please contact our technical support department.

700SRT75D _____


JOB NAME _____

NOTES _____



SPECIFICATIONS

| | |
|------------------|------------|
| PRIMARY MATERIAL | |
| SHADE MATERIAL | |
| NET WEIGHT | |
| HEIGHT | 2.2in |
| WIDTH | 5.1in |
| LENGTH | 5.1in |
| WET LISTED | |
| DAMP LISTED | |
| DRY LISTED | |
| GENERAL LISTING | ETL Listed |
| INCLUDES | |



LAMPING SPECIFICATIONS

| | LED LAMP | INTEGRATED LED | NON LED | NO LAMP |
|-----------------------------|----------|----------------|----------|---------|
| DELIVERED LUMENS | | | | |
| WATTS | | | | |
| MAX WATTAGE PER BULB | | | 75W | |
| INPUT VOLTAGE/ DIMMING TYPE | | | 120V ELV | |
| CCT | | | | |
| CRI | | | | |
| LED LIFETIME | | | | |
| L70 | | | | |
| AVERAGE BULB HOURS | | | | |
| FIELD SERVICEABLE LED | | | | |
| LAMP BASE | | | | |
| LAMP SHAPE | | | | |
| LAMP INCLUDED? | | | | |
| WARRANTY** | | | 1 Year | |

* Dimming information available at www.techlighting.com/Downloads#dimming
 ** Visit techlighting.com for specific warranty limitations and details.

T20 / T24 / JA8 INFORMATION

| | Integrated LED | Replacement LED Lamp | No Lamp * |
|--|----------------|----------------------|-----------|
| This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6 / JA8. | | | N/A |
| This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California. | | | N/A |

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

